

4 Position switch connections  
RTR ACC-0316 with cable colours  
*Alternative colour schedule shown in brackets*

		<b>Common</b>	<b>N/C</b>	<b>N/O</b>
<b>Position 0</b>	<b>Switch vertical</b>	<b>Red –</b>	<b>Brown</b>	<b>Blue</b>
		<i>(Black</i>	<i>Yellow</i>	<i>Blue)</i>
		<b>Purple –</b>	<b>White</b>	<b>Grey</b>
		<i>(Grey</i>	<i>Green</i>	<i>Red)</i>
<b>Position 1</b>	<b>Switch 45 degrees</b>	<b>Purple -</b>	<b>Grey</b>	<b>Orange</b>
		<i>(Grey</i>	<i>Red</i>	<i>Purple)</i>
		<b>Red</b>	<b>Blue</b>	<b>Black</b>
		<i>(Black</i>	<i>Blue</i>	<i>Brown)</i>
<b>Position 2</b>	<b>Switch 90 degrees</b>	<b>Black</b>	<b>Blue</b>	<b>White</b>
		<i>(Brown</i>	<i>Blue</i>	<i>Green)</i>
		<b>Orange</b>	<b>Grey</b>	<b>Brown</b>
		<i>(Purple</i>	<i>Red</i>	<i>Yellow)</i>
<b>Position 3</b>	<b>Switch 135 degrees</b>	<b>Brown</b>	<b>Orange</b>	<b>Grey</b>
		<i>(Yellow</i>	<i>Purple</i>	<i>Red)</i>
		<b>White</b>	<b>Black</b>	<b>Blue</b>
		<i>(Green</i>	<i>Brown</i>	<i>Blue)</i>

4 Position switch connections  
RTR ACC-0316  
With terminal numbers

		<b>Common</b>	<b>N/C</b>	<b>N/O</b>
<b>Position 0</b>	<b>Switch vertical</b>	<b>1</b>	<b>8</b>	<b>2</b>
		<b>5</b>	<b>4</b>	<b>6</b>
<b>Position 1</b>	<b>Switch 45 degrees</b>	<b>5</b>	<b>6</b>	<b>7</b>
		<b>1</b>	<b>2</b>	<b>3</b>
<b>Position 2</b>	<b>Switch 90 degrees</b>	<b>3</b>	<b>2</b>	<b>4</b>
		<b>7</b>	<b>6</b>	<b>8</b>
<b>Position 3</b>	<b>Switch 135 degrees</b>	<b>8</b>	<b>7</b>	<b>6</b>
		<b>4</b>	<b>3</b>	<b>2</b>